

应急广播数字收扩机

TC-1651(50W,100W)



主要特点

- 用于接收 FM\DTMB\DVB-C\IP 应急广播信号(可选)。
- 支持外部音频输入
- 支持音频切换
- 支持 WIFI，手机对音柱进行参数及数据回传
- Web 页面远程操作设置和管理。

- 支持远程音量设置和远程开关机。
- 远程自动软件升级。
- 具有无数据信号自动待机功能。
- 待机状态彻底切断功放电源，降低功耗保证终端可靠性。

技术参数

输入频率范围	111 ~ 862MHz(DVB-C)
	87.0MHz-108.0MHz (FM)
	47MHz~862MHz(DTMB)
输入电平	40 ~ 80 dB μ V(64-QAM DVB-C),
	-10 ~ -86 dBm (DTMB)
接收灵敏度	15 μ V(FM),

额定功率	50W 100W
音频频率响应	≤1dB (20Hz ~ 18KHz)
音频总谐波失真	≤1%
信噪比	≥70dB
输入电压范围	180 - 240V AC

For More Information

Please visit our website: <http://www.gospell.com> or contact your local sales representative:

GOSPELL Shenzhen, China

Overseas Sales Center
Block F10-F13, F518 Idea Land, Baoyuan road, Bao'an
Central District, Shenzhen City 518102, Guangdong
Province, China
TEL: +86-755-26716172
FAX: +86-755-29114035
E_mail: sales.dtv@gospell.com

GOSPELL Chengdu, China

Overseas Sales Subsidiary
The Fourth Floor, No. 2 Building, Matt High-Tech Industrial
Park, Tianhong Road No#5, West High-Tech Area,
Chengdu City 611731, Sichuan Province, China
TEL: +86-28-87838224
FAX: +86-28-87838304
E_mail: sales.dtv@gospell.com

GOSPELL Chenzhou, China

Headquarters
GOSPELL Industrial Park, Bai Lu Tang,
Su Xian District, Chenzhou, Hunan, China

GOSPELL India (Indian Subsidiary)

802, Filix Tower, LBS Marg, Bhandup-(W), Mum-
bai-400078, India
TEL: +91-22-66715890
E_mail: Ashish@gospell.com

GOSPELL Paraguay (Joint Office)

Tte. Garay 1795 esq. Campo Vía Barrio San Vicente CP
1615 Asunción – Paraguay
TEL: +595-21-334302
E_mail: zhouyong@gospell.com

GOSPELL Brazil (Joint Office)

Rua Engenheiro Prudente, 477/483, Sao Paulo,
Brazil
TEL: +55 (11) 2274-1455
E_mail: zhouyong@gospell.com

©2016 GOSPELL Digital Technology Co., Ltd. All rights reserved.

The GOSPELL logo is a trademark of GOSPELL Digital Technology Co., Ltd.,

All other trademarks mentioned in this document are the property of their respective owners.

Product pictures are for reference only, GOSPELL reserves the right to modify the specifications without prior notice.

