

村村响控制器

TC-1634



产品概述

TC-1634 村村响控制器主要用于村村响机房，实现应急广播适配器与村村响设备联动，能够在接收到应急广播信号时，同步将应急信号插入到原有村村响设备。应急广播结束后，解除对原有村村响设备的控制恢复本地常态广播。此设备将村村响设备与应急广播适配器进行整合，组成了完整的应急适配系统。它解决了新建应急广播同原有已建村村响系统的平滑对接问题。

主要特点

- 具备应急广播的插播功能，以及插播后常态广播的恢复功能，实现应急广播设备与村村响设备的联动。
- 具备 FM (RDS) 信号接收功能；

- 具备 FM (RDS) 信号切换功能；
- 具备多路音源控制功能。可接收应急广播、调音台、DVD、话筒等音频输入。支持 4 入 1 出音频切换功能。
- 可通过操作前面板按钮，切换到本地常态广播；
- IP 口 WEB 远程管理控制；
- GPRS 连接，传输加密控制命令；
- 支持远程在线升级

技术参数

输入接口	
输入类型 1 (FM(RDS) 输入)	频率范围:87.0MHZ-108.0MHz (步进 100KHz ; 信噪比:>60 dB ; 接收灵敏度:15μV ; 失真度:0.1-0.5% 分离度:35dB。
输入类型 2 RCA (本地多路音源及应急广播音源输入)	4 路 (L&R RCA 非平衡音频输入) 其中一路为应急广播音频输入 输入频率范围:20Hz -20KHz ; 阻抗:600Ω非平衡。
输入类型 3 (IP 输入及网管和接口)	RJ-45 10/100 Base-T 数量 : 不少于 1 个 (MPEG TS-over-IP)
输入类型 4	RS232 (村村响适配器设备级联控

输入类型 5	接口) 数量 : 1 个 (标准 RS232 接口) SMA 接收天线(GPRS 输入)
输出接口	
输出类型 1 (FM(RDS)输出)	频率范围:87.0MHZ-108.0MHz (步进 100KHz ; 信噪比:>60 dB ; 灵敏度:15μV ; 失真度:0.1-0.5% 分离度:35dB。
输出类型 2	2 个 KLONG(L&R 平衡音频输出)
输出类型 3	2 个 RCA(L&R 非平衡音频输出)
输出类型 4	村村响 FM 调制器加载接口
电源功耗	
输入电压范围	100 ~ 240V AC

输入频率范围	50/60Hz
功耗	<50W
工作环境	

工作温度范围	5°C ~ 45°C
存储温度范围	-30°C --70°C
环境湿度范围	10% - 90%

For More Information

Please visit our website: <http://www.gospell.com> or contact your local sales representative:

GOSPELL Shenzhen, China

Overseas Sales Center
Block F10-F13, F518 Idea Land, Baoyuan road, Bao'an
Central District, Shenzhen City 518102, Guangdong
Province, China
TEL: +86-755-26716172
FAX: +86-755-29114035
E_mail: sales.dtv@gospell.com

GOSPELL Chengdu, China

Overseas Sales Subsidiary
The Fourth Floor, No. 2 Building, Matt High-Tech Industrial
Park, Tianhong Road No#5, West High-Tech Area,
Chengdu City 611731, Sichuan Province, China
TEL: +86-28-87838224
FAX: +86-28-87838304
E_mail: sales.dtv@gospell.com

GOSPELL Chenzhou, China

Headquarters
GOSPELL Industrial Park, Bai Lu Tang,
Su Xian District, Chenzhou, Hunan, China

GOSPELL India ((Indian Subsidiary)

802, Filix Tower, LBS Marg, Bhandup-(W), Mum-
bai-400078, India
TEL: +91-22-66715890
E_mail: Ashish@gospell.com

GOSPELL Paraguay (Joint Office)

Tte. Garay 1795 esq. Campo Vía Barrio San Vicente CP
1615 Asunción – Paraguay
TEL: +595-21-334302
E_mail: zhouyong@gospell.com

GOSPELL Brazil (Joint Office)

Rua Engenheiro Prudente, 477/483, Sao Paulo,
Brazil
TEL: +55 (11) 2274-1455
E_mail: zhouyong@gospell.com

©2016 GOSPELL Digital Technology Co., Ltd. All rights reserved.

The GOSPELL logo is a trademark of GOSPELL Digital Technology Co., Ltd.,

All other trademarks mentioned in this document are the property of their respective owners.

Product pictures are for reference only, GOSPELL reserves the right to modify the specifications without prior notice.

